


Professional DVR with Premier Level CMS Software

- H.264 Video Compression Format
- Full HD 1080P (1920x1080) Output
- Easy DVR Setup/ Friendly GUI/ Easy Backup
- Real Time Recording (480/400fps @ CIF)
- Network: IE/CMS/3G Mobile Phone Remote
- Dual Stream Function / e-SATA supported
- Extra Alarm: HDD S.M.A.R.T., Video Loss, Recording Failure
- Support Pre-Alarm / Watermark / Bookmark search
- Daylight Saving Time / NTP
- POS function supported: Transaction Monitoring



Specification

Model		PR-2816			
Video Input (NTSC/PAL)		BNC x 16			
Video Compression Format		H.264 / (Network Transmission: H.264)			
Video Output		3xMain (HDMI, Composite & VGA) / 1xSpot (Composite)			
VGA Output		640 x 480; 800 x 600; 1024 x 768; 1280 x 1024 pixels			
Audio Input/Output		1 CH Input / 1 CH Output			
Sensor In/Alarm Out		4 / 1			
Display	Speed	480fps / 400fps			
	Resolution(pixels)	720 x 480 (NTSC) / 720 x 576 (PAL)			
	Split Screen	1 / 4 / 9 / 16 / PIP			
Recording	Resolution(pixels)	NTSC: 352 x 240 / 720x240 / 720x480, PAL:352 x 288 / 720x288 / 720x576			
	Mode	Normal, Motion, Alarm, Scheduled, Emergency Recording			
	Speed	NTSC	480fps CIF(352 x 240)	240fps 2CIF(720 x 240)	120fps D1(720x480)
		PAL	400fps CIF(352 x 288)	200fps 2CIF(720 x 288)	100fps D1(720x576)
Playback	Display	1/4/9/16			
	Search	Calendar (Date & Time), Event (Motion, Alarm), POS, Bookmark *Time bar playback via mouse			
	Speed	Normal, REW & FF (1x, 2x, 4x, 8x, 16x, 32x), Frame to Frame, Pause			
	Device	Licensed software application/ IE/ Front panel/ Remote controller/ Mouse			
Hard Disk Drive Storage		SATA HDD x 3 or SATA HDD x 2 w/DVD-RW			
Backup Device		USB2.0, DVD Writer (optional), Remote Network Backup			
Web Interface		Remote software / IE Browser / 3G Mobile Phone Surveillance Function			
PTZ Control / Port		Support Pelco-D, Pelco-P protocol / RS-485 Port / RS-232 Port			
Remote Alarm Notification		Email notification and upload to FTP site			
Network Connection		PPPoE, TCP/IP, DHCP, SMTP, DDNS			
Power		DC12V			
Accessories		IR remote controller / Mouse			



1. DVD-RW (optional)
2. Function Button
3. Control Button
4. Function Button
5. Function Button
6. Shutter (Fast Forward/Fast Backward)
7. USB Connector
8. LED Indicator
9. Channel Keypad